



**SHRI VIDHYABHARATHI MATRIC HR.SEC.SCHOOL
SAKKARAMPALAYAM , AGARAM (PO) ELACHIPALAYAM
TIRUCHENGODE(TK), NAMAKKAL (DT) PIN-637202**

Cell :99655-31727, 99655-35967,94422-88402, 80726-68664

PUBLIC EXAMINATION- MARCH- 2024

STD: XII

TENTATIVE ANSWER KEY - 08 - 03 - 2024

SUBJECT: COMPUTER APPLICATIONS

MARKS : 70

Q. NO	CONTENT	MARK
	PART-I	15X1=15
1	CHOOSE THE CORRECT ANSWER:	
1	a) Apple Inc	1
2	c) select	1
3	d) echo	1
4	b)break	1
5	d)54321	1
6	b)mysqli_close("Connection object");	1
7	b) cells	1
8	a)128	1
9	a)RJ21	1
10	b)File	1
11	b)Small and Medium-sized Enterprises	1
12	d)Debit card - Pay now	1
13	d)ICANN	1
14	a)Phishing	1
15	b)function	1
	PART - II	6X2=12
16	<ul style="list-style-type: none"> ❖ TIFF (Tagged Image File Format) ❖ BMP (Bitmap) ❖ DIB (Device Independent Bitmap) ❖ GIF (Graphics Interchange Format) ❖ JPEG (Joint Photographic Experts Group) ❖ TGA (Tagra) 	2
17	<ul style="list-style-type: none"> ❖ It is defined as the number of items that must be included in a relationship.(i.e) numberof entities in one set mapped with the number of entities of another set via the relationship. Three classifications in Cardinality are <p style="text-align: center;">❖ One-to-One</p>	2

	❖ One-to-Many ❖ Many-to-Many:	
18	<ul style="list-style-type: none"> ❖ Calling a function is another name for executing the function. A function is called simply by using the function name, along with an argument list, as a statement. <p style="text-align: center;">Syntax</p> <p style="text-align: center;">function Name(); (or) functionName(argument list);</p>	2
19	<ul style="list-style-type: none"> ❖ Communication ❖ Resource sharing ❖ Information sharing 	2
20	<ul style="list-style-type: none"> ❖ NS2 is the abbreviation of NETWORK SIMULATOR version 2. ❖ It was considered explicitly for exploration in network communication and event driven open-source simulator in computer. 	2
21	<p>DDL Commands:</p> <ul style="list-style-type: none"> ❖ CREATE - Used to create database or tables Syntax: CREATE database databasename; ❖ DROP - Deletes a database or table. Syntax: DROP database databasename; <p>DML Commands:</p> <ul style="list-style-type: none"> ❖ INSERT - Adds new rows into database table. Syntax: INSERT INTO tablename VALUES (value1, value2, value3); ❖ DELETE - Deletes the records from the table. Syntax: DELETE from tablename; 	2
22	<ul style="list-style-type: none"> ❖ Network Access Layer ❖ Internet Layer ❖ Transport Layer ❖ Application Layer 	2
23	while loop	do ... while loop
	while loop is called as the entry-check loop.	do....while loop' is called as the exit -check loop.
	The while loop first evaluates the condition before executing the code block. If the condition is true, the code block is executed. If the condition is false, the loop is terminated.	On the other hand, the do..while loop first executes the code block and then evaluatesthe condition. If the condition is true, the code block is executed again. If the conditionis false, the loop is terminated.

	The while loop may not execute the code block at all if the condition is false from the beginning.	The do..while loop, on the other hand, guarantees that the code block will be executed at least once, even if the condition is false. (any two points)
24	<p>Syntax: <code>\$file_Object= fopen("FileName","Read/WriteMode")</code> <code>or die("Error Message!");</code></p> <p>Example: <code><?php</code> <code>\$myfile = fopen("Student.txt""r") or die("Unable to open file!");</code> <code>?></code></p>	2
PART - III		6X3=18
25	<ul style="list-style-type: none"> ❖ Delivery notes ❖ Invoices ❖ Purchase orders ❖ Advance ship notice ❖ Functional acknowledgements 	3
26	<ul style="list-style-type: none"> ❖ In B2B E-Commerce, commercial transactions take place between different business organizations, through the Internet. ❖ For example, a cycle company may buy tyres from another company for their cycles. When compared to other models, the value per transaction in B2B transaction is high, because of bulk purchases. ❖ The company also might get the advantage of discounts on bulk purchases. ❖ Out-sourcing and Off-shoring are generally associated with B2B E-Commerce. 	3
27	<ul style="list-style-type: none"> ❖ Information leakage ❖ Tampering ❖ Payment frauds ❖ Malicious code threats ❖ Distributed Denial of Service(DDOS) attacks ❖ Cyber Squatting ❖ Typopiracy <p style="text-align: center;">Explain any two of the above</p>	3
28	<ul style="list-style-type: none"> ❖ A cable interconnecting two devices directly is known as a null modem cable. 	3

	<ul style="list-style-type: none"> ❖ The Crossover Ethernet cable is an example of the Null modem Cables. ❖ This cable is used to join two PCs or two network devices of the same type. <p>Example: Crossover Ethernet cable, RS232 cable, Roll over wiring.</p>	
29	<p>1. Place the cursor on the bottom handle of the second text block, click and drag the bottom handle up to the top. 2. Then place the cursor on the bottom handle of the first text block, and click and drag the bottom handle down if necessary.</p>	3
30	<ul style="list-style-type: none"> ❖ Stored value card: It is a type of debit card that is preloaded with certain amount (value), with which a payment is made. The major advantage of stored value card is that customers don't need to have a bank account to get prepaid cards. ❖ Closed loop (single purpose) ❖ Open loop (multipurpose) 	3
31	<ul style="list-style-type: none"> ❖ Semantic layer ❖ Standards translation layer ❖ Transport layer ❖ Physical layer 	3
32	<p>Syntax:</p> <pre><?php mysqli_connect("Server Name", "User Name", "Password", "DB Name"); ?></pre> <p>Example:</p> <pre><?php \$con = mysqli_connect("localhost", "my-user", "my-password", "my- db"); ?></pre>	3
33	<p>OUTPUT 1: a=>10 a=> 20 a=> 30</p> <p>OUTPUT 2: a=>10 b=> 20 c=> 20</p>	3
	PART - IV	5X5=25
34 (a)	<p>1. Click on the Polygon tool from the tool box. The cursor changes to a crosshair.</p> <p>2. Click and drag anywhere on the screen. As you drag, a Polygon appears.</p> <p>3. Release the mouse button when the Polygon is of the desired size.</p>	5

3. Choose **Element → Polygon** Settings in the menu bar.
Now Polygon Settings dialogue box appears.
4. Type 5 in the Number of sides textbox.
5. Type 50% in Star inset textbox.
6. Click OK. Now the required star appears on the screen.

(b)
(OR)

The types of EDI were constructed based on how EDI communication connections and the conversion were organized. Thus based on the medium used for transmitting EDI documents the following are the major EDI types.

- ❖ Direct EDI
- ❖ EDI via VAN
- ❖ EDI via FTP/VPN, SFTP, FTPS
- ❖ Web EDI
- ❖ Mobile EDI

Direct EDI/Point-to-Point:

- ❖ It is also called as Point-to-Point EDI. It establishes a direct connection between various business stakeholders and partners individually.
- ❖ This type of EDI suits to larger businesses with a lot of day-to-day business transactions.

EDI via VAN:

- ❖ EDI via VAN (Value Added Network) is where EDI documents are transferred with the support of third party network service providers.
- ❖ Many businesses prefer this network model to protect them from the updating ongoing complexities of network technologies.

EDI via FTP/VPN, SFTP, FTPS:

- ❖ When protocols like FTP/VPN, SFTP and FTPS are used for exchange of EDI based documents through the Internet or Intranet it is called as EDI via FTP/VPN, SFTP, FTPS.

Web EDI:

- ❖ Web based EDI conducts EDI using a web browser via the Internet. Here the businesses are allowed to use any browser to transfer data to their business partners.
- ❖ Web based EDI is easy and convenient for small and medium organizations.

Mobile EDI:

- ❖ When smart phones or other such handheld devices are used to transfer EDI documents it is called as mobile EDI.
- ❖ Mobile EDI applications considerably increase the speed of

	EDI transactions	
35 (a)	<ul style="list-style-type: none"> ❖ Patch Cable (Twisted pair) ❖ RJ45 Connector ❖ Ethernet Ports ❖ Crimping Tool <p>Patch Cable (TwistedPair):</p> <ul style="list-style-type: none"> ❖ These Cables are generally made up of 8wires in different colors. Four of them are solid colours, and the others are striped. ❖ The eight colors are white green, green,white orange, blue, white blue, orange,white brown and brown. <p>RJ45 Connector:</p> <ul style="list-style-type: none"> ❖ The RJ45 connector is a small plastic cup, which will be used to connect the wire inside the connector and ready to connect the Internet. ❖ The RJ45 connector looks similar like a telephone jack but it looks a slightly wider. The Ethernet cables are sometimes called as RJ45 cables. ❖ In RJ45 the “RJ” stands for the Registered Jack and the “45” simply refers to the number of interface standard in the cable. Each RJ45 connector has eight pins and connected to each end of the Ethernet cable. ❖ since it has 8-position, 8-contact (8P8C) modular plug, It is also known as 8P8C connector. <p>Ethernet card and Port:</p> <ul style="list-style-type: none"> ❖ Ethernet card is a Network Interface Card (NIC) that allows computers to connect and transmit data to the devices on the network. It may be an expansion card or built-in type. ❖ The Ethernet port is the jack where the Ethernet cable is to be connected. ❖ This port will be there in both the computers and the LAN port. <p>Crimping Tool:</p> <ul style="list-style-type: none"> ❖ Crimping is the process of joining two or more pieces of metal or wire by deforming one or both of them to hold each other. ❖ The crimping tool is a physical tool which is used to connect the patch wire and the Ethernet connector. 	
(b)	Proprietary Software	Open Source Software
	It is developed and tested	It is owned by the individual or

	through open collaboration.	the organization that developed it.	
	Anyone with the academic knowledge can access, inspect, modify and redistribute the source code.	only the owner or publisher who holds the legal property rights of the source code can access it.	
	The project is managed by an open source community of developers and programmers	The project is managed by a closed group of individuals or a team that developed it	5
	They are not aimed at unskilled users outside of the programming community.	The y are focused on a limited market of both skilled and unskilled end users	
	It provides better flexibility	There is a limited scope of innovation with the restrictions and all	

	Example: Android, firefoxetc	Example: Windows, MacOS	
--	-------------------------------------	--------------------------------	--

36 (a)	<p>ER models Basic concepts:</p> <ol style="list-style-type: none"> 1. Entity or Entity type 2. Attributes 3. Relationship <p>These are the general concepts which help to create an ER diagram and produce an ER model. With the help of these any database design can be created and viewed to know the concept in that database design.</p> <p>Entity or Entity type:</p> <p>An Entity can be anything a real-world object or animation which is easily identifiable by anyone even by a common man.</p> <p>Eg: In a company's database Employee, HR, Manager are considered as entities, where each of these entity will be having their own attributes. An entity is represented by a rectangular box.</p> <p>Types of Entity:</p> <ol style="list-style-type: none"> 1. Strong Entity 2. Weak Entity 3. Entity Instance <p>Strong Entity: A Strong entity is the one which doesn't depend on any other entity on the schema or database and a strong entity will have a primary key</p>	5
-----------	---	---

with it (i.e. a unique id which other entities will not have in their attributes). It is represented by one rectangle.

Weak Entity: A weak entity is dependent on other entities and it doesn't have any primary key like the Strong entity. It is represented by double rectangle.

Entity Instance: Instances are the values for the entity if we consider animals as the entity their instances will be dog, cat, cow... Etc.

Example: Human Male, Female

Attributes: An attribute is the information about that entity and it will describe, quantify, qualify, classify, and specify an entity. An attribute will always have a single value, that value can be a number or character or string.

Types of attributes:

1. Key Attribute
2. Simple Attributes
3. Composite Attributes
4. Single Valued Attribute
5. Multi Valued Attribute

Relationship Type: In ER Model, relationship exists between two entities.

Types:

- ❖ One-to-One relationship
- ❖ One-to-Many relationship
- ❖ Many-to-Many relationship

(b)
(OR)

- ❖ When the user enters the URL (consists of protocol, domain name, folder name, file name) in the browser, the system first checks its DNS cache for the corresponding IP address.
- ❖ If the IP address is found in the cache then the information is retrieved from cache. If not, then the system needs to perform DNS query i.e., the system needs to query the resolver about the IP address from Internet Service Provider (ISP).
- ❖ Each resolver has its own cache and if it is found in that then that information is retrieved. If not, then the query is passed to next domain server i.e., TLD (Top Level Domain) which reviews the request and direct the query to name servers associated with that specific domain.
- ❖ Until the query is solved it is passed to next level domains. At last the mapping and the record are returned to the resolver who checks whether the returned value is a record or an error.
- ❖ Then the resolver returns the record back to the computer browser which is then viewed by the user.

5

37

At present, there are two kinds of security authentication

(a)	<p>protocols widely used in E-Commerce, namely Secure Electronic Transaction (SET) and Secure Sockets Layer (SSL).</p> <p>Secure Electronic Transaction</p> <ul style="list-style-type: none"> ❖ Secure Electronic Transaction (SET) is a security protocol for electronic payments with credit cards, in particular via the Internet. SET was developed in 1996 by VISA and MasterCard, with the participation of GTE, IBM, Microsoft and Netscape. ❖ The implementation of SET is based on the use of digital signatures and the encryption of transmitted data with asymmetric and symmetric encryption algorithms. SET also use dual signatures to ensure the privacy. <p>Secure Sockets Layers</p> <ul style="list-style-type: none"> ❖ The most common Cryptographic protocol is Secure Sockets Layers (SSL). SSL is a hybrid encryption protocol for securing transactions over the Internet. The SSL standard was developed by Netscape in collaboration with MasterCard, Bank of America, MCI and Silicon Graphics. ❖ It is based on a public key cryptography process to ensure the security of data transmission over the internet. Its principle is to establish a secure communication channel (encrypted) between a client and a server after an authentication step. <p>Example:</p>  <p>Figure 17.3 Difference between http and https</p>	5
(b) (OR)	<p>We can define a user defined function by using the function' keyword, followed by the name of the function and a set of parentheses.</p> <p>Here is the general syntax for creating a function in PHP:</p> <p style="text-align: center;">Function definition (or declaration)</p> <p>Syntax</p> <pre style="margin-left: 40px;">function functionName([parameter list]) { // code to be executed }</pre> <p>Let's break this down</p> <ul style="list-style-type: none"> ❖ The function' keyword is used to define a function. ❖ function Name is the name of the function. It can be any valid PHP identifier, as long as it is not a reserved word. 	5

- ❖ Parameter list is a comma-separated list of variables. These parameters are optional and we can have as many or as few as we like.
- ❖ Inside the curly braces, we can put any code we want the function to execute. This can include PHP statements, loops, conditions, and so on.

Examples:**(a) Function with no parameters:**

```
<?php
    function printGreeting ()
    {
        echo "Hello, world! ";
    }
    printGreeting();
?>
```

Output : "Hello, world!".

38
(a)

- ❖ Production Manager
- ❖ Content Specialist
- ❖ Script Writer
- ❖ Text Editor
- ❖ Multimedia Architect
- ❖ Computer Graphic Artist
- ❖ Audio and Video Specialist
- ❖ Computer Programmer
- ❖ Web Master

5

Explain any 5

(b)

- ❖ **for loop**' is called as the **entry-check loop**.
- ❖ The **for loop** is used to execute a block of code a specific number of times.

Syntax:

```
for (initialization;condition; increment/decrement)
{
    //code to be executed;
}
```

(OR)

- ❖ The **initialization** part is executed only once at the beginning of the loop. It is used to initialize variables.
- ❖ The **condition** is evaluated before each iteration of the loop. If it is true, the code block is executed. If it is false, the loop is terminated.
- ❖ The **increment/decrement** part is executed after each iteration of the loop. It is used to update variables,

5

Example program:

```
<?php
    for ($i= 1;$i<=10;i++)
    {
        echo $i. "<br>";
    }
```

OUTPUT

1
2
3
4
5
6
7
8
9
10

?>

SVB NEET ACADEMY
SAKKARAMPALAYAM, ELACHIPALAYAM (Po)
TIRUCHENGODE (Tk) NAMAKKAL (Dt) 637 202

NEET CRASH COURSE & REPEATERS அடிமிழன் நடைபெறுகிறது

MBBS
INBARAJAN V
INDIRA MEDICAL COLLEGE,
TIRUVALLUR

MBBS
SANTHOSH M
GOVT. MEDICAL COLLEGE,
MADURAI

MBBS
VISHWESHWARAN G
GOVT. MEDICAL COLLEGE,
KOVAI

MBBS
SUNIL KUMAR K
GOVT. MEDICAL COLLEGE,
MADURAI

MBBS
DHARANEESH M R
GOVT. MEDICAL
COLLEGE, NAGAPATTINAM

**705
720** 2022-2023 ஆம்
ஆண்டு 12 ஆம் வகுப்பின் சாதனை LKG-XI வரை அடிமிழன் நடைபெறுகிறது.

**594
600** **583
600** 2022-2023 ஆம்
ஆண்டு 12 ஆம் வகுப்பின் சாதனை LKG-XI வரை அடிமிழன் நடைபெறுகிறது.

**664
720** 2022-2023 ஆம்
ஆண்டு 12 ஆம் வகுப்பின் சாதனை LKG-XI வரை அடிமிழன் நடைபெறுகிறது.

CELL : 99655 31727, 94422 88402



SVB நீட் பயிற்சி மையம்

தமிழ் மற்றும் ஒன்கில வழி

சக்கராம்பாளையம், அகரம், திருச்சௌங்கோடு வட்டம், நாமக்கல் மாவட்டம் - 637 202.

தமிழ்வழியில் கடந்த ஒன்டுகளில் சாதனை

சந்தோஷ M

சுனில்குமார் K

காவ்யா M

கலைவாணி A



அரசு மருத்துவக்கல்லூரி,
மதுரை.



அரசு மருத்துவக்கல்லூரி,
மதுரை.



அரசு மருத்துவக்கல்லூரி,
திருநெல்வேலி.



ஸ்ரீ முத்துக்குமரன் மருத்துவக்கல்லூரி,
சின்னை.

சக்திநேகா R

ராம்கி R

தர்வெளி C



கற்பகம் மருத்துவக்கல்லூரி,
கோவை.



PSV மருத்துவக்கல்லூரி,
காஞ்சிபுரம்.



BEST பல் மருத்துவக்கல்லூரி,
மதுரை.

2024 - 2025 CRASH COURSE & Repeaters சிறப்பம்-சாங்கள்

2017-2018 ம் ஒன்றில் நடைபெற்ற முதல் மருத்துவ கலந்தாய்வில் நமது NEET Centre ல் பயின்ற மாணவி முதல் மாணவியாக தேர்ந்தெடுக்கப்பட்டார்.

- 15 ஒன்டுகள் அனுபவமிக்க ஒசிரியர்களைக் கொண்டு பயிற்சி அளிக்கப்படுகிறது.
- அனைத்துப் பாடங்களுக்கும் முழுமையான பாடக்கறிப்புகள் தமிழிலும் வழங்கப்படும்.
- தினந்தோறும் ஒரு பாடத்தில் Slip Test- ம் வாரம்தோறும் ஒரு Cumulative Test-ம் நடத்தப்படுகிறது.
- அனுபவமிக்க ஒசிரியர்களைக் கொண்டு தயாரிக்கப்பட்ட பயிற்சி ஏடுகள் Study Material மற்றும் Previous Year Question Bank தமிழிலேயே வழங்கப்படுகிறது.
- நீட் நுழைவுக் தேர்வில் குறைவான மதிப்பெண் பெற்ற மாணவர்களை அதிக மதிப்பெண் பெற ஒரு ஒன்டு சிறப்புப் பயிற்சி அளிக்கப்படும்.
- ஒன்ற், பெண் இருபாலருக்கும் தனித்தனி விடுதி வசதி உண்டு.



SVB
NEET CAMPUS





ஷ்ரீ வித்யபாரதி

மெட்டரிக் மேல்நிலைப்பள்ளி (TM/EM)

சக்கராம்பாளையம், எலச்சிபாளையம், திருச்செங்கோடு (வ), நாமக்கல் (மா) - 637 202.

CELL : 99655 31727, 94422 88402

www.shrividhyabharathi.com

Email : vidhyabharathi.123@gmail.com

கனவுகள் மெய்யிட வேண்டும்.

தொடர்ந்து 14 ஆண்டுகளாக +2 பாதுகாக்கப்படும் நேர்வில் மாநில அளவில் சிறப்பிப்பு பெற்ற ஓரே பள்ளி...

2022-2023 ஆம் ஆண்டில் ANNA UNIVERSITY & TOP 10 ENGG. கல்லூரியில் சேர்ந்த மாணவர்கள்



ECE
SRI RAM KUMARAN N
MIT, CHENNAI



AI&DS
MOUNEESWARAN S
MIT, CHENNAI



EEE
SURAJPRASAD P
CIT COVAI



EEE
RITHESH K
PSG COLLEGE, KOVAI



B.Tech,(Food,Technology)
SANJAY K
PANNARIYAMMAN,
SATHYAMANGALAM



B.Tech
SANJAY M
GUARAGURU COLLEGE, KOVAI



B.Tech(IT)
SUJITH G
VELLAMMAL ENGINEERING
COLLEGE, CHENNAI



B.E(CSE)
GOKUL PRANESH K B
SRM COLLEGE, CHENNAI



ECE
HARISHRAGAVAN S
THIYAGAJAN COLLEGE,
MADURAI



BE(ECE)
MONISH B
INDUSTAN ENGINEERING
COLLEGE, COVAI



ECE
SANJAY S
VELLALAR COLLEGE, DINDAL



CS
MEISHANTH R
PERUNDHURAI-KONGU COLLEGE



ECE
MONISH V
POLLANCHI MAGALINGAM



BE(CSE)
KAMAL RAJ
KONGU ENGINEERING
COLLEGE, COVAI



BE(MECHATRONIC)
PRAVEEN KARTHIKEYAN D
KONGU ENGINEERING COLLEGE,
PERUNDHURAI



ECE
PRAVEEN KUMAR N
SNS COLLEGE, COVAI



BE-(AI&DS)
PRAVIN M
KONGU ENGINEERING AEDS,
PERUNDURAI



B.Tech(IT)
DEEPSHIKA S N
SRM VALLIAMMAL COLLEGE
ENGINEERING, CHENNAI



ECE
SHAJITH R
PANNARIYAMMAN,
SATHYAMANGALAM



BE(ECE)
GOKULPRASANTH
M.KUMARASAMY COLLEGE OF
ENGINEERING, KARUR



ECE
VISHWAN S
HINDHUSTHAN COLLEGE, COVAI



BE(EEE)
NIKILESH KARTHICK P
RAMAKRISHNA ENGINEERING
COLLEGE, COVAI



B.Tech(IT)
BHAVANBALJI G
PAURULI UNIVERSITY,
GUJARAT



BE(Mech)
NITIN P P
SRI KRISHNA ENGINEERING
COLLEGE, COVAI



B.Tech(IT)
NAVEENBALAJI S
PAURULI UNIVERSITY,
GUJARAT



BE(ECE)
SUDHARSEN J
INDUSTAN ENGINEERING
COLLEGE, COVAI



BE(EEE)
DHARSAN K M
POLACHI MAGALINGAM
ENGINEERING COLLEGE



AI&DS
SREENATH S
KONGU, PERUNDURAI



BE-(AI&DS)
KABILESH P S
KARUNYA UNIVERSITY,
COVAI



BE(ECE)
NIRESH KARTHIK N
KARUNYA UNIVERSITY, COVAI



BE(ECE)
MANOJ N
KARPAGAM ENGINEERING
COLLEGE, COVAI



BE-(AI&DS)
MANOJKUMAR K
KARUNYA UNIVERSITY, COVAI



BE(EEE)
KANISHKUMAR S
KARPAGAM COLLEGE OF
ENGINEERING, COVAI



BE(ECE)
MANOJ S
INDUSTAN ENGINEERING
COLLEGE, COVAI



BE-(AI&DS)
LOGAMANYAN R
KARUNYA UNIVERSITY, COVAI

SVBAdigaMai.KYAL



RAGUL S
INDUSTAN ENGINEERING
COLLEGE, COVAI



RANJITH D
CIT COLLEGE OF
ENGINEERING COVAI



SHARVESH B
VSB ENGINEERING
COLLEGE COVAI



SUJITH S
INDUSTAN COLLEGE OF
ENGINEERING, COVAI



YUVANSHANKAR S
KONGU ENGINEERING
COLLEGE, PERUNDURAI



POOJA M
KPR ENGINEERING
COLLEGE, COIMBATORE



SRI HARINI P
KARPAGAM COLLEGE OF
ENGINEERING, COIMBATORE



JEEVITHA G T
VIVEKANANDA COLLEGE OF
ENGINEERING,
ELAYAMPALAYAM



KANIKA S
VIVEKANANDA COLLEGE OF
ENGINEERING COLLEGE,
ELAYAMPALAYAM



SUBHASHREE HARINI N
VELLALAR ENGINEERING
COLLEGE, THINDAL



PRAGADHI C
MANGAIKARASI ENGINEERING
COLLEGE, MADURAI



ELAKKIYA R
PERUNDURAI KONGU
ENGINEERING COLLEGE



DHARSHINI S
KARPAGAM COLLEGE OF
ENGINEERING, COIMBATORE



HARSHINI B
KARPAGAM COLLEGE OF
ENGINEERING, COIMBATORE



KANISHKA M P
SNS ENGINEERING
COLLEGE, COIMBATORE



MADHU PRIYA P
NGP COLLEGE, COIMBATORE



MONIKA S
SRM COLLEGE OF
ENGINEERING, TRICHY



CHARUMATHI A K
JJ COLLEGE OF
ENGINEERING, TRICHY



SHANCHITHA M
M.KUMARASAMY COLLEGE
OF ENGINEERING, KARUR



VARSHA C
KALAINAR KARUNANITHI
INSTITUTE OF TECHNOLOG,
COIMBATORE



KANISHKA L
KUMARAGURU COLLEGE
OF ENGINEERING, COIMBATORE



SONIKA M
KONGU ENGINEERING
COLLEGE, PERUNDURAI



SUNITHA B
KARPAKAM INSTITUTE
OF (COIMBATORE)



NITHIKA H
KUMARAGURU COLLEGE OF
ENGINEERING, COIMBATORE



SINDHUJA R
KONGU ENGINEERING
COLLEGE, PERUNDURAI



VARSHINI P
KONGU ENGINEERING
COLLEGE, PERUNDURAI



AKSHAYA A
AVINASILINGAM,
COIMBATORE



BHUMIKA S
SALEM VINYAPPOOR
ENGINEERING



2022-2023 ஆம் ஆண்டில் PILOT & BDS & LAW கல்வூரியில் சேர்ந்த மாணவர்கள்



DEEPAKRAJ R
KERALA,
THIRUVANANDHAPURAM



CARLINE MARY A
BANGALORE CHRIST UNIVERSITY



VIDHYA K
NANDHA COLLEGE,
PERUNDURAI



THARUN A
KALASALINGAM UNIVERSITY,
VIRUTHUNAGAR



SAKTHIKUMARAN S
COUNSELLING



SUBASIVAVELAN K
SALEM VINAYAGA MISSION



MOHITH K
KAVITHA'S LAW
COLLEGE, CHENNAI

CA., B.Com., & B.B.A சேர்ந்து மாணவர்கள்



CA
HARINISRI S
KS ACADEMY
CHENNAI



CA
HARSHINI P R
V-S ACADEMY
COIMBATORE



B.COM
SASMITA A N
PSG COLLEGE, COIMBATORE



B.COM
JAIPRASATH K
SRI KRISHNA COLLEGE OF
ARTS & SCIENCE, COIMBATORE



B.COM
POORNITH R
DR. NGP ARTS & SCIENCE
COLLEGE, COIMBATORE



B.COM
RAGUVISWANATH M
PSG COLLEGE, COIMBATORE



B.COM
KAPILAN K
DR. NGP ARTS & SCIENCE
COLLEGE, COIMBATORE



B.COM
ABINESH M
SRI KRISHNA COLLEGE OF
ARTS & SCIENCE, COIMBATORE



B.COM
GAUTAM RAJENDRAN
SRI KRISHNA COLLEGE OF
ARTS & SCIENCE

+ 1 மாணவர்களுக்கான மாநில அளவிலான தமிழ்மொழி விளக்கியத் தீற்றுறித் தேர்வில் தேர்ச்சி பெற்று
Rs. 36,000/- ஊக்கத்தொகை பெறுவதற்குத் தேர்வாகியுள்ள ஸ்ரீ வித்யபாரதி சாதனையாளர்கள்

தமிழ்மொழி விளக்கியத் தீற்றுறித் தேர்வு - அக்டோபர் - 2023

ஸ்ரீநிதி பா

கீர்த்திகா வெ

தேவானந்த் ப

முகேஷ்குமார் மு

99/100

STATE 2nd RANK
Reg. No. 223120297

லத்தீகா அ.

நீவனிகா சி.பு

99/100

STATE 2nd RANK
Reg. No. 223120352

நிவாந்த் செ.

சம்ரிதா ர

99/100

STATE 2nd RANK
Reg. No. 223120274

ஸ்ரீவரிஜா மோ

கெளதும் ப

99/100

STATE 2nd RANK
Reg. No. 223120241

அனிஷ்கா ரா.ச

வர்ஷா பெ



STATE 3rd RANK

Reg. No. 223120282



Reg. No. 223120345



Reg. No. 223120260



Reg. No. 223120291



Reg. No. 223120316



Reg. No. 223120246



Reg. No. 223120334



Reg. No. 223120310



Reg. No. 223120288



Reg. No. 223120338



Reg. No. 223120340



Reg. No. 223120281



Reg. No. 223120314



Reg. No. 223120306



Reg. No. 223120293



Reg. No. 223120319

தமிழ்மொழி விளக்கியத் தீற்றுறித் தேர்வு - அக்டோபர் - 2022



95/100
திபிக்ஷா லத
Reg. No. 0551190412



89/100

அனுஶந் த

Reg. No. 0551190377



88/100

தீவ்யா செ-

Reg. No. 0551190415



87/100

சுரவனான் பா

Reg. No. 0551190285



87/100

சர்வேஸ் கோ.த

Reg. No. 0551190286



85/100

சர்விகா.சு

Reg. No. 0551190397



83/100

மிதுன்குமார் வெ.ஞா

Reg. No. 0551190340



81/100

போகித் ம

Reg. No. 0551190360



81/100

நவநினா.த

Reg. No. 0551190417



81/100

ராஸ்மிகா.பு.ரா

Reg. No. 0551190441



80/100

பிரித்தீகா.மோ.ம

Reg. No. 0551190427

ஸ்ரீ வித்யபாரதி

மெட்டிக் மேல்நிலைப்பள்ளி

கலைகள் மெய்யீடு வேல்டும். சுக்கராம்பாளையம், எச்சிபாளையம், திருச்செங்கோடு(வ), நாமக்கல் (மா) - 637 202.

www.shridhyabharathi.com

Email : vidhyabharathi.123@gmail.com

2024 - 2025 ஆம் கல்வியாண்மீற்கான KG முதல் XII வரை அடிமிழன் நடைபெறுகிறது

பள்ளியின் சிறப்பம்சங்கள்:

- ❖ FOUNDATION, NEET, JEE, UPSC ,OLYMPIAD (For VI to XII)
- ❖ குழந்தைகளுக்கு விளையாட்டு மூலம் கற்றல் கற்பித்தல் (Play Way Method)
- ❖ Montessori தரத்தில் கற்றல் கற்பித்தல் நடைபெறுகிறது.
- ❖ KG குழந்தைகளுக்கு தரமாகவும், சுவையாகவும் மதிய உணவு வழங்கப்படுகிறது.
- ❖ KG - II Std வரை CBSE கற்பித்தல் முறை பிஸ்பற்றப்படுகிறது.
- ❖ சிறந்த மூச்சிய கையெழுத்துப்பயிற்சி (தமிழ், ஆங்கிலம் மற்றும் ஹந்தி) அளிக்கப்படுகிறது.
- ❖ சிறப்பாக ஆங்கிலத்தில் பேசும் பயிற்சி (Communicative English) அளிக்கப்படுகிறது.
- ❖ ஒவ்வொரு மாணவர் மீதும் களிவான தனிகவனம் செலுத்தப்படுகிறது.
- ❖ கதை, கவிதை, கட்டுரை, ஓவியம் மற்றும் பேச்சாற்றலுக்கான சிறப்பு பயிற்சி அளிக்கப்படுகிறது
- ❖ தமிழ், ஆங்கிலம், ஹந்தி வாசித்தல் திறனை மேம்படுத்தும் வகையில் பயிற்சிகள் அளிக்கப்படுகிறது.
- ❖ ஹந்தி தேர்வுகளுக்கு (ப்ராதமிக், மத்யமா, ராவுப்பாலா) தேர்வு மையமாக செயல்படுகிறது.
- ❖ ஒவ்வொரு வரு திறுத்திலும் புரிந்து தேர்வு (Understanding Test) நடைபெறுகிறது.
- ❖ பாடவாரியாக Club அமைத்து Activity நடைபெறுகிறது .
- ❖ சிலம்பம், வில்வித்தை, கராந்தே, பரதம், மேற்கத்திய நடனம், துப்பாக்கிச்சுடுல் ஆகிய Extracurricular Activity வகுப்புகள் சிறந்த முறையில் நடைபெறுகிறது.
- ❖ Education Oriented Field Trip அமைத்துச் செல்லப்படுகிறது.
- ❖ Computer பயிற்சி சிறந்த முறையில் அளிக்கப்படுகிறது.
- ❖ மன அமைதி மற்றும் நூபக சுக்தியை மேம்படுத்துவதற்காக யோகா வகுப்புகள் நடத்தப்படுகிறது.
- ❖ மாணவர்கள் Chess ல் சிறந்து விளங்க Chess வகுப்புகள் சிறந்த முறையில் நடைபெறுகிறது.
- ❖ ஒவ்வொரு பருவத் தேர்வு திறுத்திலும் School Level Achievement Survey - Test நடத்தப்படுகிறது.
- ❖ மாணவர்களின் உடல் திறனை மேம்படுத்தும் வகையில் விளையாட்டுப் பயிற்சிகள் (Indoor And Outdoor Games) அளிக்கப்படுகிறது.



செல்: 99655 31727, 99655 35967, 94422 88402, 80726 68664

DEPARTMENT OF COMPUTER SCIENCE

SHRI VIDHYABHARATHI MATRIC HR.SEC.SCHOOL

SVBAdGAMAI.NET